How to use MDB-RS232® to test NV11 Bill recycler

Firstly, Must be familiar with the ITL vadlidator manager to setup the bill acceptor to enable the recycler and setup what type bill will be received to bill recycler

Enable the features to support recycler and then change the NV11 to MDB interface

ITL Validator	Manag	ger 4.6										- 0	\times
ITL	V a l	lidator	Man	a g	e r				C	Contact (Js About	Configure	Exit
	-										Oser Mode	Advanced	``
Name	Port	Address	Home		R	un	Options	F	Program	Co	mmands	Modify D	ataset
NV11 PLUS COM4 0			Device Details										
Connected Connected Device Info Device NV11 Type Note Float Serial Numbers Primary Validator 3562726 Note-Float 3667928 Firmware Version NV113640000CY1 Firmware Issue 3.64 Passed Encryption Yes			Device Details Name NV11 PLU Serial Number 3562726 Type Note Floa Supports Note Pay Passed Encryption Yes Build Revision 0.0 Connection			n/Pay Out	Firm Versii Issue Host Inter Dat Versii High Curre		ware NV113640000CY1 3.64 Protocol 7 aces SSP, MDB aset on CNY06E17 est Channel 6 incles CNY				
Build Revision Nos			Channel	Country		Denomination	Route		Stored in Payout		Enabled		
Device	rice 0.0		1	CNY		1.00	Cashbox	0			Yes		
Note-Float	te-Float 0.0		2	CNY		5.00	Cashbox	Cashbox		0			
Interfaces	S	SP, MDB	3	CNY		10.00	Payout		0		Yes		
Determined	-	W00017	4	CNY		20.00	Cashbox		0		Yes		
Dataset Version Currencies	c	NY06E17 NY	5	CNY		50.00	Cashbox		0		Yes		_
Detect Devices			0	CNY		100.00	Cashbox		0		Tes		
	Add D	evice											
Di	isconne	t Device											

- 1. Enable the features to support recycler 37010000002
- 2. Read back the recycler setup

3703

Reply: **00 04 04** (Indicates what bill types can be routed to the Recycler dispenser) Then you will know which type of the bill will be received to recycler

- 3. Recycler enable

the 03 position, according to the data returned by 3703

Now we start to test the bill recycler and Put a bill that will be accepted to bill recycler, will received data, for example: **30 B2 29**

(From this data, that means bill type is **02**, and received to bill recycler)

4. Send a command to dispense the recycler bill

3706020001 02 is the bill type, should be the same as received data type

5. Dispense value command

3707000A 000A is the value of bills to be paid out

For above command, the type of bill that need to be paid out must be the same as the type that can be entered in the Recycler, or NV11 will reply FF